

User Manual

Intel LGA1156 (i3 / i5) - Igloo 1100 CU Series

Igloo 1100 CU Series (Fan with 1B1S Bearing)

Igloo 1100 CU (E) Series (Fan with Entering Bearing)

Igloo 1100 CU (2B) Series (Fan with Two-Ball Bearing)




Inspiring Cooling Technology
www.GlacialTech.com



•Installation




Step 1
Remove the plastic cover.



Step 2
Place the fasteners at the motherboard's holes.




Step 3 (Error!)
Make sure that all the fasteners are at the original status.



Step 4
Push down on the top of fasteners, you should hear a "click" when pushing down the fastener.



(Error!)
Do not put hands on the top of fan as the pressing point by installation in order to avoid fan hub damage.



Step 5
Connect the fan cable connector to the motherboard CPU fan header.

- FAN APPROVED BY CE & TUV & UL
- The specifications are subject to change without notice. All brand names and trademarks are the properties of their respective owners.

For further information, please consult our website: www.GlacialTech.com

© 2009 GlacialTech Inc. All rights reserved.

•Specifications

Model	Igloo 1100 CU Silent / (E) / (2B)	Igloo 1100 CU Light / (E) / (2B)	Igloo 1100 CU / (E) / (2B)	Igloo 1100 CU PWM / (E) / (2B)	
Socket Type	LGA1156 (i3 / i5)				
Cooler Dimension (mm)	Ø95 × 67				
Cooler Weight (gram)	475				
Fan	Rated Voltage	DC 12 V			
	Type	1B1S / (Entering Bearing) / (Two-Ball Bearing)			
	Dimension (mm)	80 × 80 × 25			
	Speed (RPM)	2,000 (±10%)	2,600 (±10%)	3,200 (±10%)	800 (±300 rpm) ~ 3,600 (±10%)
	Airflow (CFM)	26.0 (±10%)	35.5 (±10%)	44.1 (±10%)	50.08 (Max.)
	Noise (dBA)	20	25	32	15 ~ 38
Interface Material	High Efficiency Thermal Compound				